



\* Dimensions are in mm.

## Configuration

Connector Type	2.92mm Female
Connector Impedance	50 Ohms
Connector Polarity	Standard
Waveguide Style	WR34
Flange	FBP260
Adapter Body Style	Right Angle

## Electrical Specifications

Frequency	21.7 to 33 GHz
Insertion Loss (dB)	≤0.4
Return Loss/VSWR	1.2 to 33GHz

## Materials Information

Body	Brass Sprayed With Ice Grey Paint
------	-----------------------------------

## Environmental Data

Temperature Range	-40°C to +105°C
2011/65/EU(RoHS)	Compliant

While the information has been carefully compiled to the best of our knowledge, nothing is intended as representation or warranty on our part and no statement herein shall be construed as recommendation to infringe existing patents. In the effort to improve our products, we reserve the right to make changes judged to be necessary.