



*Dimensions are in mm

Configuration

Connector Type	2.92 FeMale
Connector Impedance	50 Ohms
Connector Polarity	Standard
Waveguide Style	BJ320(WR28)
Flange	FBP320
Adapter Body Style	Right Angle

Electrical Specifications

Frequency	26.3 to 40 GHz
Insertion Loss (dB)	$\leq 0.1 \times \sqrt{f_{\text{GHz}}}$
VSWR /Return Loss	1.25 to 40GHz

Materials Information

Center Contact	CuBe Gold Plated
Outer Contact	Brass Gold Plated
Body	Brass Gold Plated
Dielectric	PEI

Environmental Data

Temperature Range	-40°C to +165°C
2002/95/EC(RoHS)	Compliant

While the information has been carefully compiled to the best of our knowledge, nothing is intended as representation or warranty on our part and no statement herein shall be construed as recommendation to infringe existing patents. In the effort to improve our products, we reserve the right to make changes judged to be necessary.