
## ADAPTOR DATASHEET



## 2.4(MALE)-2.4(FEMALE)

## **2.4-JWKS**



\*Dimensions are in mm

Configuration		
Connector 1 Type	2.4mm Male	
Connector 1 Impedance	50 Ohms	
Connector 1 Polarity	Standard	
Connector 2 Type	2.4mm Female	
Connector 2 Impedance	50 Ohms	
Connector 2 Polarity	Standard	
Connector Mount Method	None	
Adapter Body Style	Right Angle	
Frequency Insertion Loss (dB)	DC to 50 GHz ≤ 0.08 xSqt.(f_GHz)	
Electrical Specification	ns 	
INSCRUON LOSS (UB)	≤ U.U8 X5ql.([_GMZ)	
VCMD /Datuma Laga	1 25 +- 50 611-	
VSWR /Return Loss	1.25 to 50 GHz	
·		
·	1	
Materials Information	1	
Materials Information Center Contact	CuBe Gold Plated & Brass Gold Plated	
Materials Information Center Contact Outer Contact	CuBe Gold Plated & Brass Gold Plated Stainless Steel	
Materials Information Center Contact Outer Contact Body	CuBe Gold Plated & Brass Gold Plated Stainless Steel Stainless Steel	
Materials Information Center Contact Outer Contact Body Dielectric	CuBe Gold Plated & Brass Gold Plated Stainless Steel Stainless Steel	
Materials Information Center Contact Outer Contact Body Dielectric Environmental Data	CuBe Gold Plated & Brass Gold Plated Stainless Steel Stainless Steel PEI&PTFE	

While the information has been carefully compiled to the best of our knowledge, nothing is intended as representation or warranty on our part and no statement herein shall be construed as recommendation to infringe existing patents. In the effort to improve our products, we reserve the right to make changes judged to be necessary.

Gwave Technology Inc.	
4th Floor, New Material Plaza, You	ngfeng Hi-Tech Base,Haidian
District, Beijing , China (100094)	www.gwave-tech.com

Tel.: +86 10 86484190 Fax: +86 10 86484190-0 email: gwave@gwave-tech.com

Page

1/1