
ADAPTOR DATASHEET



2.92MM(MALE)-2.4MM(FEMALE) RIGHT ANGLE

2.92/2.4-JWKS



*Dimensions are in mm

configuration	
Connector 1 Type	2.92mm Male
Connector 1 Impedance	50 Ohms
Connector 1 Polarity	Standard
Connector 2 Type	2.4mm Female
Connector 2 Impedance	50 Ohms
Connector 2 Polarity	Standard
Connector Mount Method	None
Adapter Body Style	Right Angle
Frequency	DC to 40 GHz
Frequency	
Insertion Loss (dB)	≤ 0.08 xSqt.(f_GHz)
<u> </u>	
Insertion Loss (dB)	≤ 0.08 xSqt.(f_GHz) 1.25 to 40 GHz
Insertion Loss (dB) VSWR /Return Loss	≤ 0.08 xSqt.(f_GHz) 1.25 to 40 GHz
Insertion Loss (dB) VSWR /Return Loss Materials Information	≤ 0.08 xSqt.(f_GHz) 1.25 to 40 GHz
Insertion Loss (dB) VSWR /Return Loss Materials Information Center Contact	≤ 0.08 xSqt.(f_GHz) 1.25 to 40 GHz CuBe Gold Plated & Brass Gold Plated
Insertion Loss (dB) VSWR /Return Loss Materials Information Center Contact Outer Contact	≤ 0.08 xSqt.(f_GHz) 1.25 to 40 GHz CuBe Gold Plated & Brass Gold Plated Stainless Steel
Insertion Loss (dB) VSWR /Return Loss Materials Information Center Contact Outer Contact Body	≤ 0.08 xSqt.(f_GHz) 1.25 to 40 GHz CuBe Gold Plated & Brass Gold Plated Stainless Steel Stainless Steel
Insertion Loss (dB) VSWR /Return Loss Materials Information Center Contact Outer Contact Body Dielectric	≤ 0.08 xSqt.(f_GHz) 1.25 to 40 GHz CuBe Gold Plated & Brass Gold Plated Stainless Steel Stainless Steel

While the information has been carefully compiled to the best of our knowledge, nothing is intended as representation or warranty on our part and no statement herein shall be construed as recommendation to infringe existing patents. In the effort to improve our products, we reserve the right to make changes judged to be necessary.

Gwave Technology Inc.	Te
4 th Floor,New Material Plaza,Yongfeng Hi-Tech Base,Haidian	
District, Beijing , China (100094) www.gwave-tech.com	er

Tel.: +86 10 86484190 Fax: +86 10 86484190-0 email: gwave@gwave-tech.com

Page

1/1