
ADAPTOR DATASHEET



N(MALE)-3.5MM(FEMALE)

N/3.5-JK



*Dimensions are in mm

Configuration		
Connector 1 Type	N Male	
Connector 1 Impedance	50 Ohms	
Connector 1 Polarity	Standard	
Connector 2 Type	3.5mm Female	
Connector 2 Impedance	50 Ohms	
Connector 2 Polarity	Standard	
Connector Mount Method	None	
Adapter Body Style	Straight	
Fraguenay	DC to 10 CUz	
Electrical Specification	ns	
Frequency	DC to 18 GHz	
Insertion Loss (dB)	≤ 0.1 xSqt.(f_GHz)	
Insertion Loss (dB) VSWR /Return Loss	≤ 0.1 xSqt.(f_GHz) 1.15 to 18 GHz	
Insertion Loss (dB) VSWR /Return Loss	≤ 0.1 xSqt.(f_GHz) 1.15 to 18 GHz	
Insertion Loss (dB) VSWR /Return Loss Materials Information	≤ 0.1 xSqt.(f_GHz) 1.15 to 18 GHz	
Insertion Loss (dB) VSWR /Return Loss Materials Information Center Contact	≤ 0.1 xSqt.(f_GHz) 1.15 to 18 GHz CuBe Gold Plated	
Insertion Loss (dB) VSWR /Return Loss Materials Information Center Contact Outer Contact	≤ 0.1 xSqt.(f_GHz) 1.15 to 18 GHz CuBe Gold Plated Brass Gold Plated	
Insertion Loss (dB) VSWR /Return Loss Materials Information Center Contact Outer Contact Nut	≤ 0.1 xSqt.(f_GHz) 1.15 to 18 GHz CuBe Gold Plated Brass Gold Plated Stainless Steel	
Insertion Loss (dB) VSWR /Return Loss Materials Information Center Contact Outer Contact Nut Dielectric	≤ 0.1 xSqt.(f_GHz) 1.15 to 18 GHz CuBe Gold Plated Brass Gold Plated Stainless Steel	

While the information has been carefully compiled to the best of our knowledge, nothing is intended as representation or warranty on our part and no statement herein shall be construed as recommendation to infringe existing patents. In the effort to improve our products, we reserve the right to make changes judged to be necessary.

Gwave Technology Co.,Ltd.

No.33 Building,Hanjiachuan Yard,Haidian District,Beijing
China(100094) www.gwave-tech.com

Tel.: +86 10 62450051/52 Fax: +86 10 62450053 Email: gwave@gwave-tech.com Page

1/1