
CONNECTOR DATASHEET



1.85MM STRAIGHT PLUG

1.85-JWB2



*Dimensions are in mm

onnector 1 Type	1.85mm Male
Connector 1 Impedance	50 Ohms
Connector 1 Polarity	Standard
Body Style	Right Angle
Connector Mount Method	None
Connector 2 Interface Type	086 Series
Cable Attachment Method	Solder
Insertion Loss (dB)	< 0.05 xSat.(f GHz)
Frequency	DC to 67 GHz
Insertion Loss (dB) VSWR /Return Loss	≤ 0.05 xSqt.(f_GHz) 1.30 to 67 GHz
VSWR /Return Loss	
VSWR /Return Loss Materials Information	1.30 to 67 GHz
VSWR /Return Loss Materials Information Center Contact	1.30 to 67 GHz CuBe Gold Plated
VSWR /Return Loss Materials Information Center Contact Outer Contact	1.30 to 67 GHz CuBe Gold Plated Stainless Steel
VSWR /Return Loss Materials Information Center Contact Outer Contact Body	1.30 to 67 GHz CuBe Gold Plated Stainless Steel Stainless Steel
VSWR /Return Loss Materials Information Center Contact Outer Contact	CuBe Go
VSWR /Return Loss Materials Information Center Contact Outer Contact Body Dielectric	1.30 to 67 GHz CuBe Gold Plat Stainless Steel
VSWR /Return Loss Materials Information Center Contact Outer Contact Body	1.30 to 67 GHz CuBe Gold Plated Stainless Steel Stainless Steel

While the information has been carefully compiled to the best of our knowledge, nothing is intended as representation or warranty on our part and no statement herein shall be construed as recommendation to infringe existing patents. In the effort to improve our products, we reserve the right to make changes judged to be necessary.

Gwave Technology Inc.	
4th Floor, New Material Plaza, Yo	ngfeng Hi-Tech Base,Haidian
District, Beijing , China (100094)	www.gwave-tech.com

Tel.: +86 10 86484190 Fax: +86 10 86484190-0 email: gwave@gwave-tech.com Page

1/1