

Waveguide to Coax Adapters

Gwave

WR-42 to 2.92mm Female Right Angle Waveguide to Coax Adapters with UBR220 Flange, 18-26.5GHz

WR42/2.92-UBR220-K-V







Dimensions are in mm

| Product Configuration | |
|---------------------------|-------------|
| Body Style | Right Angle |
| Flange Designation | UBR220 |
| Waveguide Size | WR-42 |
| Connector Series | 2.92mm |
| Connector Polarity | Standard |
| Connector Gender | Female |
| Connector Impedance (Ohm) | 50 |
| | |
| Electrical Specifications | |
| VSWR | 1.2 |

| Insertion Loss | ≤0.25 |
|-----------------|------------|
| Frequency Range | 18-26.5GHz |
| Mechanical Data | |
| Weight | 17.55 |
| Body Material | Aluminum |

Enviromental Specifications

| RoHS Compliant | Yes |
|-----------------------------|------------------|
| Operating Temperature Range | -30 °C to +70 °C |

NOTE:information herein is believed by Gwave to be accurate. However, Gwave assumes no responsibility for any omissions or errors inaccuracies for its use or for any infringements of patents or other rights of third parties that may result from its use. Data is intended for informational purpose only and does not constitute a contract of sale or any express or implied warranty, including any warranty of merchat ability or fitness for a particular purpose.